

Application

A battery operated, single or four station controller for situations where automatic control is required but power is not available, is difficult or expensive to procure.

Features

- Fully waterproof and submersible (to 2m, per IP68 standard) cabinet.
- Mount directly on to valve, wall or valve box wall.
- 1 and 4 station configurations.
- Flip cover protects large LCD display.
- Two independent programs.
- "Water Budget" 10 to 200% (in 10% increments).
- Program start time stacking.
- Low battery power indicator.
- Watering times: 1 minute to 9 hours, 59 minutes, in 1 minute increments.
- Start times: 3 starts per program
- Manual and semi-automatic starts.
- Multiple watering day options – 7 day calendar or up to 14 day interval.
- Rain off function.
- Irritrol latching solenoid (DCL) and 2400 MTF included with the 1 station model, waterproof wire connectors included.
- New screwed cap / o-ring battery compartment.
- Mounting bracket included.
- Easy 4 button programming.
- Smart "Reserve Power" feature will not allow activation without sufficient power to deactivate.

Specifications

- Uses one 9 volt alkaline battery
- Operates 2 wire 9 volt DC coils (Irritrol DCL or Toro DCLS-P)

Dimensions

(without mounting bracket)

Height 125mm

Width 100mm

Depth 45mm

Valve Compatibility

- DCL suits all Irritrol valves and Toro 220, P220, P150 and Ez-Flo Plus™ Solenoid valves.



Junior DC Controller



DCL

Ordering Details

Code	Description
JRDC – 1A	Single station Junior DC controller complete with 9 VDC latch coils and 2400MTF valve
JRDC – 4	Four station Junior DC controller only
DCL	DCL Potted Latching Solenoid, 6-24 VDC